

Add: Carspa Building, Xinhejia Industrial Zone, Baishi, Yueqing, Wenzhou, Zhejiang, China 325604

Tel: 86-577-61778999, 62767199

Fax: 86-577-62767299

E-mail: info@chinacarspa.com info@carspa.cn

Website: www.carspa.cc

Pure Sine Wave DC to AC Power Inverter - P Series

P600-241

P600-481

Inverter Expert P600-600W with USB

P600-121


- Features:
- Input & output fully isolated. ◀
 - With USB output port ◀
- **High Surge:** High surge current capability starts difficult loads such as TVS, **◄** camps, motors and other inductive loads.
 - **Soft start:** Smooth start-up of the appliances. ◀
 - Pure Sine Wave Output Waveform: Clean power for sensitive loads. ◀
 - AC output identical to, and in some cases ◀
 - better than the power supplied by your utility.
 - **Cooling Fan:** Control by load or temperature (optional) ◀

P600-242

Low Total Harmonic Distortion: below 3% ◀



P600-482



P600-122



E8 Rohs (E 2 LIMITED WARPANTY

■ SPECIFICATION:

MODEL.

			1 000-2-1	1 000-401	1 000-122	1 000-242	1 000-402
OUTPUT	AC VOLTAGE		100/110/120VAC			220/230/240VAC	
	RAT ED POWER	600W					
	SURGE POWER	1200W(for few seconds)					
	USB	5V, 2.1A					
	WAVEFORM	Pure Sine Wave(THD<3%)					
	FREQUENCY	$50/60$ Hz ± 3 Hz					
	AC REGULATION	±5%					
	STANDARD RECEPTACLES	A, B, C, D, E, F, G, H, I, GFCI(optional as above)					
	LED INDICATOR	Green for power on, red for failure / protection status indication					
INPUT	NO LOAD CURRENT DRAW	≤0.7A					
	DC VOLTAGE	12V	24V	48V	12V	24V	48V
	VOLTAGE RANGE	10.5~15.0VDC	21.0-30.0V DC	42~60V DC	10.5~15.0VDC	21.0-30.0V DC	42~60V DC
	EFFICIENCY (Typ.)	>87.0%	>90.0%	>90.0%	>90.0%	>90.0%	>90.0%
	FUSE	40A*2	20A*2	10A*2	40A*2	20A*2	10A*2
	DC CABLE	BVR4*2	BVR4*2	BVR4*2	BVR4*2	BVR4*2	BVR4*2
PROTECTION	BAT.LOW ALARM	11±0.5V DC	22±1V DC	44±2V DC	11±0.5V DC	22±1V DC	44±2V DC
	BAT.LOW SHUTDOWN	10.5±0.5V DC	21.0±15V DC	42±2V DC	10.5±0.5V DC	21.0±1V DC	42±2V DC
	OVERLOAD	Shutdown					
	OVER VOLTAGE	14.8±0.5V DC	29.6±1V DC	58.4±2V DC	14.8±0.5V DC	29.6±1V DC	58.4±2V DC
	OVER TEMPRETURE	Shut-off output voltage, recover automatically after temperature goes down					
	SHORT CIRCUIT	Shut-off output voltage, repower on to recover					
	BAT.REVERSE POLARITY	By fuse open					
	SOFT START	Yes 5~10s					
	EARTH LEAKAGE	Yes					
ENVIRONMENT	RESET VOLTAGE AFTER LVS	11.8~12.8V DC	23.6~25.6V DC	47.2~51.2V DC	11.8~12.8V DC	23.6~25.6V DC	47.2~51.2V DC
	WORKING TEMP.	0-40℃					
	WORKING HUMIDITY	20%-90% RH non-condensing				Soft High Start Efficiency	Turbo
SAFETY & EMC	STORAGE TEMP.& HUMIDITY	-30℃-70℃ 22°F-185°F、10-95%				Start 10 Efficiency	Cooling ran
	EMC	Compliance to EMC Directive 2014/30/EU					
	LVD	Compliance to LVD Directive 2014/35/EU				Universal Protection Circuit Circuit	
	ROHS	Compliance to EU 2015/863 2011/65/EU				Circuit	Over-temperature
	EMARK	Compliance to ECE R10.05:2014					
	IEC	Compliance to IEC62368				Compact Des	ign
OTHERS	DIMENSION	260*150*77.7mm					
	PACKING	2.1Kg, 6pcs/15.6Kgs/Ctn(57*30.5*30cm)					
	COOLING FAN	Control by load/temperature(optional)				Low Interference	Taabualaay
	APPLICATION	Home and office appliances, Power tools and portable equipments, Vehicle and solar power systemsetc.				Low Interference	reciniology
INSTALL	ATION					New Energ	y Solution
		#SB€## PURE SINE V	AC LOAD—			+ 100% pure sine better than p	Mobile AC Source